

Out Put Current are measured on unscreened cable, Used Tool:- Clip on meter(Meter Type- Kyoritsu KEW-2117R)

CCR Brilliancy Step and CCR input current variation with Tap setting

	Circuit	Supply Voltage (V)	Brilliancy step`	Tap position	Input Current (A)	Output Voltage (V)	Circuit on load output current (A)	Status
CCR – 1	WRE	418 V	S1	100%	19.20	235	2.20	✓
			S2		21.10	272	2.50	✓
			S3		24.21	326	2.80	✓
			S4		29.03	438	3.40	✓
			S5		35.11	578	4.10	✓
			S6		45.24	835	5.20	✓
			S7		59.05	1225	6.60	✓

CCR – 1	WRE	418 V	S1	50%	9.00	230	2.20	✓
			S2		10.94	278	2.50	✓
			S3		12.00	326	2.80	✓
			S4		14.82	433	3.40	✓
			S5		17.89	578	4.10	✓
			S6		22.00	835	5.20	✓
			S7		27.85	1220	6.60	✓

DIVALUX

R.G.SILVA. A.G.L Engineer
R.G.S.

Agustino

Amir
(S. AMIR THARAS)
02/04/19


CCR - 2	ERE & TWY	418 V	S1	100%	20.00	415	2.20	✓
			S2		22.74	463	2.50	✓
			S3		25.40	523	2.80	✓
			S4		30.80	641	3.40	✓
			S5		37.00	803	4.10	✓
			S6		47.00	1122	5.20	✓
			S7		59.60	1586	6.60	✓


CCR - 2	ERE & TWY	418 V	S1	70%	13.01	517	2.20	✓
			S2		15.00	577	2.50	✓
			S3		17.00	625	2.80	✓
			S4		20.01	728	3.40	✓
			S5		25.12	863	4.10	✓
			S6		33.02	1132	5.20	✓
			S7		47.06	1580	6.60	✓


CCR - 3	PAPI - 06	415 V	S1	50%	10	70	2.17	✓
			S2		11	86	2.50	✓
			S3		13	96	2.80	✓
			S4		15	129	3.40	✓
			S5		19	172	4.10	✓
			S6		24	253	5.20	✓
			S7		30	361	6.60	✓

CCR - 3	PAPI - 24	415 V	S1	50%	10	70	2.17	✓
			S2		11	86	2.50	✓
			S3		13	96	2.80	✓
			S4		15	129	3.40	✓
			S5		19	171	4.10	✓
			S6		24	251	5.20	✓
			S7		30	360	6.61	✓

DIVALUX

R.G. SILVA. AGL Engineer





 CS-AMIRTHARAJ
 02/04/19